技术要求

1.物料号：SW1A7030EB010

2.产品名称：KN1开关中性英文说明书

3.材质：125克铜版纸

4.尺　：60*80mm

60.00 mm

80.00 mm



INSTRUCTIONS

The Handheld Self-Powered Wireless Switch

Product Description

The Handheld Self-Powered Wireless Light Switch is a battery-free wireless transmitter that communicates with a wide variety of receivers. Every time one of the switches is pressed a small micro-generator produces a small electrical current that powers a built-in transmitter. This transmitter sends wireless signals that command the receiver to turn a device off or on. With an appropriate receiver, the switch can also be used to control the dimming of lights.

Product Parameters

Work Type: Push Button Type
Number of keys: 1,2,4keys
Power Supply: Self-powered(No battery)
Working Frequency: 433MHz
Working Temperature: -20°C~+55°C
Control Distance: 80m (outdoor) 25m (indoor)
How to use : Pairing with Wireless Receiving Controller

Pair with Controller

The KN1 series switches need to be paired with wireless receiving controller, and suppor t two ways to pair: Ordinary pairing and d irectional pairing.

（1）Ordinary pairing

The ordinary pairing method is to press and hold the controller "pairing key" for about 3 seconds, release the "pairing key" button when the indicator light flashes, and then press a button of the KN1 switch once . The indicator light goes off, which means that the pairing is successful. Then you can control the wireless controller by this button.

If the controller is a dimmable model and the dimming mode is on, long press on the paired button to dim the brightness circularly and remember the brightness when you turn on the light again.

（2）Directional Pairing

In order to meet the user's habits of the switch and to ensure that the multiple controllers can be turned on and off at the same time in the one-to-multiple mode, we design the directional pairing mode on a two-button switch. The ordinary pairing method is to press and hold the "pairing key" on the controller for about 3 seconds and release when the light is flashing. Then press one of the KN1 series 2 gang switches button four times (within 1 seconds), the indicator light goes off, which means pairing is successful. After directional pairing is successful, the left button can only turn off and the right button can only turn on. Long press the left button can only dim, long press the right button can only brighten.

(more detailed steps,please refer to the receiving controller instruction)



CERTIFICATE INSPECTED